

Digital Arrester Clamp Tester

Leakage & Harmonics Current Measurements For Arresters

Model ALCL-40L



GENERAL

Lightning arresters are designed to protect a power distribution system by shunting to ground the high voltage surges caused by lightning. ALCL-40L measures to warn that an arrester is damaged or deteriorated and should not be energized.

FEATURES

- ALCL-40 is designed to test the diagnostic of **OXIDE SURGE ARRESTER**
- The least influence from the external magnetic field and noise by triple shielding for CT
- Compliant with IEC6099-5
- Enabled the measurement for 100nA resolution and harmonics current
- Motor operation for opening/closing of the jaw with extensional ABS glass fiber insulation rod

SPECIFICATIONS

CT Sensor

CT : ϕ 40mm
Opening/closing of the jaw : Motor operation
Withstanding voltage : AC 2300V, 1 minute (Between the core of CT and CT outer case)

Measuring and display unit

Measuring function : Leakage current, Harmonic current (Fundamental & third harmonics)
Measuring method : Dual slope integration mode
Measuring range : AC 0-300 μ A/3mA/30mA (3 range manual)
Input frequency : 45-60Hz (Fundamental frequency)
AC conversion : AC coupled true rms responding
Display : LCD Max. 3200 count
Sampling : 2 times/sec.
Over indication : "OL" mark on LCD
Low battery indication : "Low" mark on LCD
Data hold indication : "DH" mark on LCD
Auto power off function : Approx. 10 minutes later after power on
Power supply : AA size alkaline battery x 4
Limitation of circuit voltage : Less than 500V AC
Operating temperature : 0-40°C, less than 80%RH, w/o condensation
Storage temperature : -10~60°C, less than 70%RH, w/o condensation
Dimensions : 160(W)×950(L)×84(D) (When retracted)
: 160(W)×2680(L)×84(D) (When stretched)
Weight : Approx. 2.6kgs

AC Current

Accuracy (23°C \pm 5°C, less than 80%RH)

Range	Resolution	Accuracy (45~65Hz)	Max. input Current
300 μ A	100nA (0.1 μ A)	* $\pm 1.2\% \pm 8$ digit	40A rms
3mA	1 μ A (0.001mA)		
30mA	10 μ A (0.01mA)		

Crest factor : <3 (0-50% of the range)
: <2 (50-100% of the range)

Harmonic Current Measurement (Fundamental & third harmonics)

Measuring method : PLL method
Minimum fundamental input : More than 3% of full scale in each range
Accuracy : (1% \pm 5 digit) \pm (Basic accuracy of ACA)
– (error by neighboring harmonics)

*Accuracy specified : More than 4% harmonics are necessary against fundamental harmonics

Accessories : CT cover case.....1
Instruction manual..... 1